

User Guide

Hard Disk Option

Trademarks

The following are trademarks or registered trademarks of their respective owners. Other product names mentioned in this manual may also be trademarks or registered trademarks of their respective owners. Registered trademarks are registered in the United States Patent and Trademark Office; some trademarks may also be registered in other countries. PostScript is a trademark of Adobe Systems Incorporated for a page description language and may be registered in certain jurisdictions.

Adobe, Adobe PhotoShop, Adobe PageMaker/Adobe Systems Incorporated

Microsoft, MS-DOS, Windows/Microsoft Corporation

Proprietary Statement

The digitally encoded software included with your printer is copyrighted. All Rights Reserved. This software may not be reproduced, modified, displayed, transferred, or copied in any form or in any manner or on any media, in whole or in part, without the express written permission of the manufacturer.

Copyright Notice

This manual is copyrighted. All Rights Reserved. This manual may not be copied in whole or in part, nor transferred to any other media or language, without the express written permission of the manufacturer.

The specifications of your printer and the content of this publication are subject to change without prior notice. Every attempt has been made to verify the accuracy of the content herein

GEG-99161

How This Guide is Organized

Chapter 1 - Installing the Hard Disk Option in the Printer

This chapter explains the procedure for installing the Hard Disk Option in color laser printer.

Chapter 2- Using the Hard Disk Option

This chapter discusses the available control panel menus when the Hard Disk option is installed. Power-on files and the storage of files on the Hard Disk option are also discussed.

Chapter 3- Troubleshooting

This chapter discusses troubleshooting error messages appearing on the printer's control panel. Sources of help, information and technical support are also discussed.

Features of the Hard Disk Option

The Hard Disk Option for your printer provides the following:

- Quick and easy installation requiring no tools
- 2.1 GB capacity
- Storage of PostScript files and/or storage of PCL power-on files
- Control panel menus enable fast and easy file manipulation.

Safety Precautions



CAUTION: Handling ESD-Sensitive Parts

Many electronic parts use parts that are known to be sensitive to electrostatic discharge (ESD). To prevent damage to ESD-sensitive parts, follow the instructions below in addition to all the usual precautions, such as turning off power before removing logic boards:

- Keep the ESD-sensitive part in its original shipping container (a special “ESD bag”) until you are ready to install the part into the machine.
 - Make the least-possible movements with your body to prevent an increase of static electricity from clothing fibers, carpets, and furniture.
 - Use an ESD wrist strap on your wrist if available. Connect the wrist band to the system ground point. This discharges any static electricity in your body to the machine.
 - Hold the ESD-sensitive part by its edge connector cover; do not touch its pins. If you are removing a pluggable module, use the correct tool.
 - Do not place the ESD-sensitive part on any metal surface; if you need to put down the ESD-sensitive part for any reason, first put it into its special bag.
 - Metal surfaces are electrical grounds. They increase the risk of damage because they make a discharge path from your body through the ESD-sensitive part. (Large metal objects can be discharged paths without being grounded.)
 - Prevent ESD-sensitive parts from being accidentally touched by other personnel.
 - Take extra care working with ESD-sensitive parts when cold weather heating is used because low humidity increases static electricity.
-



WARNING: To prevent the danger of electric shock, before installing any options be sure to turn the power switch of the printer to the off [O] position and disconnect the power cord from the wall outlet.

Contents

How This Guide is Organized iii

Features of the Hard Disk Option iii

Safety Precautions iv

Chapter 1 Installing the Hard Disk in the Color Printer

About this Chapter 1-2

Installing the Hard Disk Option in Color Laser Printer Printers 1-2
2-2

Chapter 2 Using the Hard Disk Option

About this Chapter 2-2

Control Panel MENU Structure 2-2

Using the Disk Menu 2-3

Using the PCL and PostScript Power-On Files Feature 2-3

Power-on Files Defined 2-3

Using the FLASH SIMM or Hard Disk Option as a PostScript Device 2-4

Device Names and Priority 2-4

PostScript Operators 2-4

Device Parameter Sets 2-4

Warmstart.ps and Sys/Start Files 2-5

Chapter 3 Troubleshooting

About this Chapter 3-2

Obtaining Help and Information 3-2

Your Point of Purchase 3-2

Your Application Vendor 3-2

Technical Support 3-2

Chapter 1

Installing the Hard Disk in the Color Laser Printer

In this Chapter . . .


- “About this Chapter” on page 1-2
- “Installing the Hard Disk Option in the Color Laser Printer” on page 1-2

About this Chapter


This chapter explains the procedure for installation of the Hard Disk option in the color laser printer.

Installing the Hard Disk Option in the Color Laser Printer


1. Carefully review the safety precautions in the front of this guide before starting this installation procedure.
2. Ensure that the printer power switch is set to the OFF [O] position.



3. Disconnect the power cord from the wall outlet.



4. Turn thumbscrews on controller assembly counterclockwise until loose and gently pull controller assembly towards you to remove from printer.




5. Locate the area of the controller identified as “Hard Disk”. Align the hard disk within the designated area and gently move up to ensure the 44-pin male connector of the hard disk is connected to the 44-pin female connector on the controller assembly.



6. The hole in the hard disk four mounting screws should be aligned with the holes in the back of the controller. Insert the plastic rivet through the aligned holes. If you fail to align the hard disk with-


1-4 | Hard Disk Option User Guide
Installing the Hard Disk Option in the Color Laser Printer

in the designated outlined area for the hard drive placement, the four mounting holes for the four screws will NOT line up. If there is improper alignment, remove the Hard Drive and reinstall.




NOTE: Improper alignment will damage the hard drive and possibly the controller board.


7. Reinstall the controller assembly. Once firmly in place, push and hand tighten the thumb-screws in a clockwise direction.



8. Connect the power cord to the wall outlet.



9. Turn the printer power switch to the ON [I] position.



The installation of your Hard Disk option in your printer is now complete. Proceed to [“Using the Hard Disk Option”](#) on page 2-1

...

Chapter 2

Using the Hard Disk Option

In this Chapter . . .

- “About this Chapter” on page 2-2
- “Control Panel MENU Structure” on page 2-2
- “Using the Disk Menu” on page 2-3
- “Using the PCL and PostScript Power-On Files Feature” on page 2-3
- “Using the FLASH SIMM or Hard Disk Option as a PostScript Device” on page 2-4

About this Chapter

This chapter discusses the available control panel menus when the Hard Disk option is installed. Power-on files and the storage of files on the Hard Disk option are also discussed.

Control Panel MENU Structure

When the Hard Disk option is installed, the printer control panel menu structure is enhanced as shown in the following table. The shaded areas denote additional features and settings relevant to the Hard Disk option.

Menu				
	Paper Menu			
	Interface Menu			
	PS Menu			
	PCL Menu			
	System Menu			
		Display Language		
		Alarm Control		
		Power Saver		
		Wait Timeout		
		Job Timeout		
		Jam Recovery		
		Hex Print		
		Toner Out		
		Power-On Files		
			Playback	FILE01.POR
				FILE02.POR
				FILE03.POR
				...
				...
			Delete	FILE01.POR
				FILE02.POR
				FILE03.POR
				...
				...
	Quality Menu			
	Functions			
	Disk Menu			
		Print		
		Delete		
		Format Disk		
		Disk Summary		

NOTE:

1. The Flash Menu and Disk Menu will only appear when the respective FLASH SIMM and/or Hard Disk option is installed.
2. Power-On Files menu will only appear if either a FLASH SIMM or a Hard Disk option is installed and power-on files exist.

Using the Disk Menu

Manipulation of files stored on the hard disk option can be accomplished using the Disk Menu.

Disk Menu	
	Print
	Delete
	Format Disk
	Disk Summary

Print

This selection will read the selected file from the Hard Disk and print it as if it were being received from one of the input ports.

Delete

This selection will delete the selected disk file or directory from the hard drive. To delete an entire directory, you must first delete all the files within that directory.

Format Disk

This selection will reformat the hard drive.



All files on the hard drive will be deleted if this function is selected.

Disk Summary

This selection will print a page containing information about the hard disk drive including a list of all the current existing files and directories.

Using the PCL and PostScript Power-On Files Feature

Power-on Files Defined

If an optional FLASH SIMM or Hard Disk option is installed in your printer, your printer has the capability of storing additional power-on files which can be read and interpreted at power-on.

Power-on files can contain either PCL or PostScript language content. Examples of power-on files include soft fonts, and macro/overlay definitions. The FLASH SIMM can store approximately 8MB of file storage, the hard disk drive storage depends on the size of the drive that is installed in your printer.

NOTE: Power-on files are processed at power-on initialization only and not at the start of every print job.

Contact the technical support organization at your point of purchase for full details about the power-on files feature.

Using the FLASH SIMM or Hard Disk Option as a PostScript Device

In order to allow PostScript programs to access the FLASH SIMM and/or hard disk options, a full implementation of a PostScript storage device is provided. This section discusses an overview of the PostScript operators and parameter sets that are included in the support.

For detailed information on using the operators/parameter sets, please refer to the following publications:

PostScript Language Reference Manual
Adobe PostScript 3 Version 3010 Product Supplement

Device Names and Priority

The device names assigned to the FLASH SIMM and hard disk options are as follows:

%flash%	device name for the FLASH SIMM
%disk0%	device name for the hard disk

If both devices are installed, both devices can be referenced uniquely by name. If no device name is specified in the PostScript operation, the *SearchOrder* parameter in the device parameter set establishes the priority for file operations. When both devices are installed, the *SearchOrder* value for the hard disk is set to 1, while the *SearchOrder* value for the FLASH SIMM is set to 2. This gives priority to the hard disk.

PostScript Operators

All of the standard file-object related operators (file, read, write, etc) are supported. In addition, following is a list of device-related PostScript Compatibility operators that are supported for use with the FLASH SIMM(%flash%) or hard disk (%disk0%) options:

- devdismount
- devforall
- devformat
- devmount
- devstatus
- diskonline
- diskstatus
- initializedisk
- dosysstart
- setdosysstart

Device Parameter Sets

When installed, a device parameter set will be supported for either or both FLASH SIMM and hard disk options. The parameter sets can be referenced using the device names %flash% or %disk0%. Each parameter set will include the following parameters:

- LogicalSize

- Writeable
- BlockSize
- Searchable
- SearchOrder
- Type
- Mounted
- HasNames
- PhysicalSize
- InitializeAction
- Free
- Removable

Warmstart.ps and Sys/Start Files

When either or both the FLASH SIMM or hard disk options are installed, there are two features which provide support for automatic execution of a PostScript program during power-on initialization.

The first feature is the *warmstart.ps* file. Each time the printer is powered on, either or both optional storage devices will be checked for a file named *warmstart.ps*. If this file is found, it will be read and parsed by the PostScript interpreter. It is up to the PostScript programmer to create the content of this file and get the file onto the storage device using the PostScript device and file operators.

The second feature is the *Sys/Start* file. If either or both of the optional storage devices are installed, an additional parameter will be supported in the System Parameter set. This parameter is an integer parameter called *StartupMode* and is set to 1 by default.

NOTE: This parameter can be read or written using the *dosysstart* and *setdosysstart* operators.

Each time the printer is powered on, if the *StartupMode* parameter is set to 1, either or both the optional storage devices will be searched for a file called *Sys/Start*, a file named *Start* in a path called *Sys*. If this file is found, it will be read and parsed by the PostScript interpreter. Again, it is up to the PostScript programmer to create the content of this file and get the file onto the storage device using the PostScript device and file operators.

...

Chapter 3

Troubleshooting

In this Chapter . . .

- “About this Chapter” on page 3-2
- “Obtaining Help and Information” on page 3-2
- “Technical Support” on page 3-2

About this Chapter

This chapter discusses sources of help, information and technical support.

Obtaining Help and Information

Several sources of help and information are available, depending on the type of help you need:

Your Point of Purchase

Your local vendor from whom you purchased this printer may be best equipped to help you. Your vendor has specially trained service technicians available to answer questions and the equipment to analyze your printer problems.

Your Application Vendor

Often, “printing” problems have more to do with the application being used than with the printer. In this case, the application manufacture is the best source of help.

Technical Support

Technical Support is available world-wide. Please refer to your point of purchase for the appropriate contact in your area.

When calling for assistance, please have the following information readily available:

- Your phone number, fax number and shipping address.
- A description of the problem.
- The printer model.
- The type of host computer you are using.
- The type and version of operating system you are using.
- The application and version you are using.
- The interface you are using (e.g., network, parallel, serial).
- If using the network interface, the network protocol (TCP/IP, EtherTalk, IPX/SPX, NetBIOS/NetBEUI).
- The printer emulation you are using (e.g., PCL or PostScript).
- A printout of your printer's Configuration Summary. (Refer to your printer's *User* manual).
- If you have a printer hardware problem you cannot resolve, provide the error message displayed on the Control Panel. For a list of error messages, refer to your printer's *User* manual.

NOTE: To confirm that a problem is isolated to the Hard Disk option, you may want to remove the Hard Disk option from the printer and diagnose the printer using the User's Manual that came with your printer. If the condition persists, it can be assumed that the problem resides within the printer and not necessarily the Hard Disk option.
